


User Manual

URL: www.eregister.wbsetcl.in

- **Home Page**



Digital Log Register

STEP 1:

- **Creation of New Sub-Station Entry:**

- Go to Master Data-> Create New Sub-Station
- It will Ask for Default User ID and Password (As per Figure) and Press "Login" Buton. [Ask IT Department, WBSETCL- Shri. Abir Dutta for Default Log in Credential](#) or Refer to Circular.

The screenshot shows the login form of the WBSETCL system. At the top, there's the WBSETCL logo. Below it, there's a text input field with the placeholder text "Init01". Below that, there's a password input field with a toggle icon. At the bottom, there's a large blue button labeled "Login".

- After Login Enter the details of the
 - ✓ Tr Zone, Area Office, Sub-station (From Drop Down Menu)
 - ✓ Email and Mobile No (Should be valid Sub-station in charge Mail Id and Official Mobile No which will be used for further approval process through OTP)
 - ✓ No of voltage class can be added/removed dynamically by pressing the +/- Button respectively and enter the class (e.g. 132 KV, 220 KV Etc.).
 - ✓ Provide New Password and Confirm Password for generating further Login credential.
 - ✓ Tick the 'Disclaimer' and 'SAVE' the details.

 West Bengal State Electricity Transmission Company Limited A Government of West Bengal Enterprise CIN No. U40101WB2007SGC113474		Towering Heights বিদ্যুৎ সংবহন রথে, Illuminating Lives বাহালা এখন আলোর পাথে Transmitting Happiness	
Sub-Station and Operational Voltage Class Details Form			
Choose Transmission Zone :	Kolkata		
Choose Area Office :	Kasba		
Select Your Sub-Station Name :	Kasba 220 KV		
Enter Valid Email Assigned to this Sub-Station:	abir_wbsetcl@yahoo.com		
Enter Mobile Number Assigned to this Sub-Station:	9932703413 (10 digit number) (Please Do Not Forget this Mobile No. & E-mail Id , As it is Mandatory for Password Recovery & Log Register APPROVAL Process)		
Voltage Class :	132 KV Voltage Class + 220 KV Voltage Class -		
New Password			
Confirm Password			
☒ Please Check the Details Carefully Before Proceed. Once Click on "Save" Button Rectification of Details are Not Possible. N.B. By Clicking on "SAVE" Button, you will be and you will be logged off. For Further Transaction you have to Re- login with New Password.			
SAVE Reset			

- After Saving it will show the Successful message new credential for further Login will be-

User Id: Registered full Mail Id (e.g.- abir_wbsetcl@yahoo.com)
Password: New password

STEP 2:

• Creation of New Equipment

- Go to Master Data-> Creation of New Equipment Details
- Login Using Newly Generated Credentials.
- Now you can add Multiple Equipment/Bay for Multiple voltage class (Available for that SS) by pressing 'Save and Enter Next Voltage class wise Equipment' Button after entering details of the Bay as shown in Figure.

For Example: -

Choose the Voltage class 132 KV and

- Complete Entry of all Equipment entry for 132 KV 'BUS'.
- Then Complete Entry of all Equipment entry for 132 KV 'Feeder' and so on.

Now Change the Voltage Class to 220KV and

- Complete Entry of all Equipment entry for 220 KV 'Coupler'.
- Then Complete Entry of all Equipment entry for 220 KV 'Transformer' and so on.

- User can add or Remove equipment name as per requirement and after entering all details of the equipment 'Logout' (Top Right Corner of the Page) from the Page.



West Bengal State Electricity Transmission Company Limited
A Government of West Bengal Enterprise
CIN No. U40101WB2007SGC113474

Towering Heights
Illuminating Lives
Transmitting Happiness

বিস্ময় সংবহন রথে,
বাংলা এখন আলোর গথে

[Log Out](#)

Bay Details Form

Sub-Station Name:

Voltage Class :

Bay Type :

Please Use Different Equipment Name during Insertion (e.g.- First Transformer- 150 MVA Tr. No. 1; 2nd Transformer 150 MVA Tr. No. I or 160 MVA Tr. No. 4 may be written as 160 MVA Tr. No. IV etc.), Otherwise Updation of field will be erroneous.

[Add More Bay](#)

☐ Please Check the Details Carefully Before Proceed. Once Click on "Save" Button Rectification of Details are Not Possible.

[Save and Enter Next Voltage class wise Bay](#)

[Reset](#)

Update / Modify or Rename Existing Equipment of Kasba 220 KV Sub-Station:

Existing Bay Details:

Modification / Shifting Bay Details:

Provide the Sequence of Bay For Ease of Panel Wise Reading Entry (Must Be Digit. e.g.- 1,2,3... etc.) :

[Modify Bay Details](#)

Add More Voltage Class Kasba 220 KV Sub-Station:

[Add Voltage Class](#) User Can Also Add Existing / New Voltage Class if They Forgot to Enter The Voltage Class Earlier :

- Rectification of Existing Equipment (If Required)**

Go to the Update / Modify Section of the Equipment Entry Page (Applicable for installation of new equipment / if you forgot to enter the equipment in earlier stage)-

Update / Modify or Rename Existing Equipment of Kasba 220 KV Sub-Station:

Existing Bay Details:

Modification / Shifting Bay Details:

Provide the Sequence of Bay For Ease of Panel Wise Reading Entry (Must Be Digit. e.g.- 1,2,3... etc.) :

[Modify Bay Details](#)

Now select the Equipment from the left panel and change the detail in middle panel-

- Intended Equipment Name
- Bay Type of the Equipment
- New Voltage class to which the equipment belongs to
- Bay / Panel sequence in which reading is taken in the concern sub-station- Required to maintain for ease of reading entry. All the Equipment must have panel sequence starting from 1 to higher number. Panel sequence 1 will come first in the log register page.

- **Addition of New Voltage Class (If Required)**

If you forgot to entry the voltage class in earlier stage you can add new voltage from the bottom section of the equipment page.

Add More Voltage Class Kasba 220 KV Sub-Station:

--- Select ---

Add Voltage Class

User Can Also Add Existing / New Voltage Class if They Forgot to Enter The Voltage Class Earlier :

STEP 3:

- **Creation of Log Register:**

- Go to Register-> Log register & Login
- Enter the details like Timeslot, Value of the Parameters etc under **Digital Log Register** Tab.



West Bengal State Electricity Transmission Company Limited
A Government of West Bengal Enterprise
CIN No. U40101WB2007SGC113474

Towering Heights | বিদ্যুৎ স্রবহন রাস্থে,
Illuminating Lives | বাহালা এখান আলোর গাথে
Transmitting Happiness

Log Out

Details of Parameters and value Input Section for Log Register:

Sub-Station Name:

Kasba 220 KV

Select Date:

14-01-2025

Digital Log Register
Weather Register
Transformer TAP Register
Offline Excel Upload (Log Register)

Digital Log Register

You Can SAVE the Digital Log Register Data as a Draft by Pressing CTRL+S (or 'Save As Draft' Button). After Entering all Data for the Selected TimeSlot You can SAVE Finally, But Once Finally SAVED No Further Modification Will be Allowed

Select Time Slot for Log Entry: 11-12 Hrs

←

Serial Number	Bay Type	Bay Name	Parameters	Enter value of Parameter
1	132 KV TRANSFORMER	132 KV 150 MVA TR. NO. I	R-AMP	
2	132 KV TRANSFORMER	132 KV 150 MVA TR. NO. I	Y-AMP	
3	132 KV TRANSFORMER	132 KV 150 MVA TR. NO. I	B-AMP	
4	132 KV TRANSFORMER	132 KV 150 MVA TR. NO. I	MW	
5	132 KV TRANSFORMER	132 KV 150 MVA TR. NO. I	MVA	
6	132 KV TRANSFORMER	132 KV 150 MVA TR. NO. I	MVAR	
7	220 KV FEEDER	Kasba- CESC-1	R-AMP	
8	220 KV FEEDER	Kasba- CESC-1	Y-AMP	
9	220 KV FEEDER	Kasba- CESC-1	B-AMP	

- One can save the data as a Draft (Partially save) using short cut key 'CTRL+S' or by pressing "SAVE as Draft" Button.
- Once you feel full data for log register for a particular timeslot is completed tick on the disclaimer button at below

☐

Please Check the Details Carefully Before Proceed.

of the page , which allow you to modify the entered data for one last time. Now if you feel all data for this time slot is absolutely correct then you can Save the Data for the selected Timeslot Permanently using "**Final SAVE Digital Log Register**" button and enter data for further timeslot in same process. Remember once you finally saved the data you can not modify the data anymore.

- Kindly Enter the **Weather Details End of Each Shift** (e.g.- Morning shift data entry Time: 13-14 Hrs; Evening shift data entry Time: 21-22 Hrs and Night shift data entry Time: 05-06 Hrs). First Enter the data of Night Shift then enter data One cannot enter the Morning Shift Data and Evening Shift data. i.e-

Night Shift-> Morning Shift-< Evening Shift



West Bengal State Electricity Transmission Company Limited
A Government of West Bengal Enterprise
CIN No. U40101WB2007SGC113474

Towering Heights | বিদ্যুৎ স্রবহন রথে,
Illuminating Lives | বাংলা এখন আলোর পথে
Transmitting Happiness

[Log Out](#)

Details of Parameters and value Input Section for Log Register:

Sub-Station Name:

Select Date :

[Digital Log Register](#) | [Weather Register](#) | [Transformer TAP Register](#) | [Offline Excel Upload \(Log Register\)](#)

Weather Register

Kindly Fill the Details Related to the Shift Wise Weather: (Shift wise details can be enter during end of each Shift, e.g- Night shift data entry Time: 05-06 Hrs; Morning shift data entry Time: 13-14 Hrs and Evening shift data entry Time: 21-22 Hrs)

Select Time Slot for Log Entry:

Shift	Weather (Maximum 40 Character)	Report to Comm System (D.P.C)	Report to Comm System (P&T)
Night Shift			
Morning Shift			
Evening Shift			

Without Entering **Night Shift** Data of the Day, You are Unable to Insert data for Morning or Evening Shift Data

☐ Please Check the Details Carefully Before Proceed. Once Click on "Save" Button Rectification of Details are **Not Possible**.

Save Weather Register
Reset

- Now Save the Data using “**Save weather Register**” button for the selected Timeslot and enter data for further timeslot in same process
- Kindly Enter the **Transformer TAP Details End of DAY**. Opening Balance and closing balance will be automatically evaluated, you have to enter the TAP count only.



West Bengal State Electricity Transmission Company Limited
A Government of West Bengal Enterprise
CIN No. U40101WB2007SGC113474

Towering Heights | বিদ্যুৎ স্রবহন রথে,
Illuminating Lives | বাংলা এখন আলোর পথে
Transmitting Happiness

[Log Out](#)

Details of Parameters and value Input Section for Log Register:

Sub-Station Name:

Select Date :

[Digital Log Register](#) | [Weather Register](#) | [Transformer TAP Register](#) | [Offline Excel Upload \(Log Register\)](#)

Transformer TAP Register

Kindly Fill the Details of All Transformer TAP Related Data: All Three Data- Opening, TAP & Closing) Should Enter at a Time (Preferably at the Day End)

Transformer Name	Opening Balance of TAP Counter	No. of TAP Operations During The Day	Closing Balance of TAP Counter
132 KV 150 MVA TR. NO. I	0	Enter TAP Count	
132 KV 160 MVA TR. NO. III	0	Enter TAP Count	
132 KV 160 MVA TR. NO. IV	0	Enter TAP Count	
220 KV 150 MVA TR. NO. I	0	Enter TAP Count	
220 KV 150 MVA TR. NO. II	0	Enter TAP Count	
220 KV 160 MVA TR. NO. III	0	Enter TAP Count	
220 KV 160 MVA TR. NO. IV	0	Enter TAP Count	

☐ Please Check the Details Carefully Before Proceed. Once Click on "Save" Button Rectification of Details are **Not Possible**.

Save TAP Register
Reset

- Now Save the Data using “**Save TAP Register**” button for the selected Timeslot and enter data for further timeslot in same process.
- **Excel Upload for Offline Data Entry (Applicable where Internet is not available for long period of time)**
 - First you have to download the template of Digital log form Dashboard->Download (Excel). Now fill the offline data into the downloaded excel sheet without altering the existing details already present the template. Enter only ‘Parameter value’ column in first sheet and other details in second sheet. **DO NOT touch the exiting data that are already present in the downloaded template.**



West Bengal State Electricity Transmission Company Limited
A Government of West Bengal Enterprise
CIN No. U40101WB2007SGC113474

Towering Heights
Illuminating Lives
Transmitting Happiness

বিদ্যুৎ সংবহন রথে,
বাংলা এখন আলোর পথে

Dashboard

Log Register

Event Register

Download Log Register

Download Event Register

Download (Excel)

Reports

Logout

[Download Event Register](#)

Sub-Station Name:

Select Start Date :

Select End Date : Select Date in the Format of YYYY-MM-DD (e.g., 2024-01-17)

DOWNLOAD

Downloaded Excel Sheet will be Saved at "Download" Folder. Keep the File in Safe Place for Archival Process.

Remember Only Sanctioned Log Register Between Selected Dates Will Be Downloaded

TEMPLATE: Download Excel Template (Saved at "Download" Folder) for Uploading Digital Log Register Data During Non-Availability of Internet **DOWNLOAD**

- Once data entry is complete save the excel sheet and upload as shown in figure-

Digital Log Register Weather Register Transformer TAP Register Offline Excel Upload (Log Register)

Upload Offline Log Register Data from Excel Sheet (Applicable When Internet Not Available)

Choose File **Upload Offline**

- After Data Entry Completion "Logout" form the page.

STEP 4:

- Dashboard (To View the Entered Data):**

After Login Form Dashboard user can view the **non-approved** (Draft) version of Log Register, Weather Register, Transformer Register for the Selected Date. You can also find he other register like Event register from the left panel.

To see the **Log register** choose the date and press on 'SHOW' button then click on the relevant register TAB below-



West Bengal State Electricity Transmission Company Limited
A Government of West Bengal Enterprise
CIN No. U40101WB2007SGC113474

Towering Heights
Illuminating Lives
Transmitting Happiness

বিদ্যুৎ সংবহন রথে,
বাংলা এখন আলোর পথে

Dashboard

Log Register

Event Register

Download Log Register

Download Event Register

Download (Excel)

Reports

Logout

[Digital Log Register](#)

Sub-Station Name:

Select Date : Select Date in the Format of YYYY-MM-DD (e.g., 2025-01-15)

SHOW Choose the Day, Press on "SHOW" Button & Click on the Register Below

Digital Log Register Weather Register Transformer TAP Register

Selected Date: 2025-01-14 (Draft Copy of Digital Log Register)

Serial #	Timeslot	Voltage Classwise Bay	Bay Name	Parameter Name	Parameter Value
1	05-06 Hrs	132 KV TRANSFORMER	132 KV 150 MVA TR. NO. I	B-AMP	3
2	05-06 Hrs	132 KV TRANSFORMER	132 KV 150 MVA TR. NO. I	MVA	5
3	05-06 Hrs	132 KV TRANSFORMER	132 KV 150 MVA TR. NO. I	MVAR	6
4	05-06 Hrs	132 KV TRANSFORMER	132 KV 150 MVA TR. NO. I	MW	4
5	05-06 Hrs	132 KV TRANSFORMER	132 KV 150 MVA TR. NO. I	R-AMP	1
6	05-06 Hrs	132 KV TRANSFORMER	132 KV 150 MVA TR. NO. I	Y-AMP	2
7	05-06 Hrs	132 KV BUS	132 KV 150 MVA TR. NO. II	B-R	21
8	05-06 Hrs	132 KV BUS	132 KV 150 MVA TR. NO. II	R-Y	19
9	05-06 Hrs	132 KV BUS	132 KV 150 MVA TR. NO. II	Y-B	20
10	05-06 Hrs	132 KV TRANSFORMER	132 KV 160 MVA TR. NO. III	B-AMP	30
11	05-06 Hrs	132 KV TRANSFORMER	132 KV 160 MVA TR. NO. III	MVA	32
12	05-06 Hrs	132 KV TRANSFORMER	132 KV 160 MVA TR. NO. III	MVAR	33
13	05-06 Hrs	132 KV TRANSFORMER	132 KV 160 MVA TR. NO. III	MW	31



West Bengal State Electricity Transmission Company Limited

A Government of West Bengal Enterprise

CIN No. U40101WB2007SGC113474

Towering Heights

Illuminating Lives

Transmitting Happiness

বিন্দুৎ সংবহন রথে,

বাংলা এখন আলোর পথে

Dashboard

Log Register

Event Register

Download Log Register

Download Event Register

Download (Excel)

Reports

Logout

Digital Log Register

Sub-Station Name:

Select Date :

Select Date in the Format of YYYY-MM-DD (e.g., 2025-01-13)

SHOW Choose the Day, Press on "SHOW" Button & Click on the Register Below

Digital Log Register

Weather Register

Transformer TAP Register

Selected Date: 2025-01-14 (Draft Copy of Weather Register)

Shift Wise Weather Details of 2025-01-14

Shift	Weather	Report to Comm System (D.P.C)	Report to Comm System (P&T)
Night Shift	100	101	102
Morning Shift	200	201	202
Evening Shift	300	301	302

Important Switching Operations

Excellent Reading



West Bengal State Electricity Transmission Company Limited

A Government of West Bengal Enterprise

CIN No. U40101WB2007SGC113474

Towering Heights

Illuminating Lives

Transmitting Happiness

বিন্দুৎ সংবহন রথে,

বাংলা এখন আলোর পথে

Dashboard

Log Register

Event Register

Download Log Register

Download Event Register

Download (Excel)

Reports

Logout

Digital Log Register

Sub-Station Name:

Select Date :

Select Date in the Format of YYYY-MM-DD (e.g., 2025-01-13)

SHOW Choose the Day, Press on "SHOW" Button & Click on the Register Below

Digital Log Register

Weather Register

Transformer TAP Register

Selected Date: 2025-01-14 (Draft Copy of Transformer TAP Register)

Details of All Transformer TAP Related Data of 2025-01-14

Transformer Name	Opening Balance of TAP Counter	No. of TAP Operations During The Day	Closing Balance of TAP Counter
132 KV 150 MVA TR. NO. I	5	5	5
132 KV 160 MVA TR. NO. III	10	10	10
132 KV 160 MVA TR. NO. IV	15	15	15
220 KV 150 MVA TR. NO. I	20	20	20
220 KV 150 MVA TR. NO. II	25	25	25
220 KV 160 MVA TR. NO. III	30	30	30
220 KV 160 MVA TR. NO. IV	35	35	35

STEP 5:

Approve Log Register

- First Select the Date for which approval is required and click on “Show” Button and select “Digital Log Register” TAB To view the Draft Version first.
- Now Click on the “Approve Digital Log Register” Button at the bottom of the page.

74	05-06 Hrs	Other Parameters	Battery Charging AMP 110 V Bank 1	93
75	05-06 Hrs	Other Parameters	Battery Charging AMP 110 V Bank 2	94
76	05-06 Hrs	Other Parameters	Battery Charging AMP 110 V Bank 3	95
77	05-06 Hrs	Other Parameters	Battery Charging AMP 220 V Bank 1	96
78	05-06 Hrs	Other Parameters	Battery Charging AMP 220 V Bank 2	97
79	05-06 Hrs	Other Parameters	Battery Charging AMP 220 V Bank 3	98
80	05-06 Hrs	Other Parameters	Battery Charging AMP 220 V Bank 4	99
81	05-06 Hrs	Other Parameters	Battery Charging AMP 220 V Bank 5	100

Approve Digital Log Register

Station-Incharge can Approve the Logsheet of the Day by Sending OTP in their Registered Email ID

- A 6-Digit OTP will be delivered to the registered E-mail ID of the Substation (There may be a time gap for delivering the OTP due to mail server response relay). Kindly look int the SPAM/JUNK folder too for the OTP. For the time being OTP will be displayed at the top of the page.

New OTP: 838268



West Bengal State Electricity Transmission Company Limited
A Government of West Bengal Enterprise
CIN No. U40101WB2007SGC113474

Approve Log Register
Logout

Enter the 6 Digit OTP :


APPROVE

- Then 'Approve' the Log Register for the Selected Date.

STEP 6:

Download PDF version of Log Register

User can Download the PDF version of Log Register once the Log Register of any Particular Date, which is approved by the Station in-Charge by OTP validation Approach by clicking in the” **Download Log Register**” Button at the side panel of the Page.

Dashboard
Log Register
Event Register
Download Log Register
Download Event Register
Download (Excel)
Reports
Logout

Download Log Register

Sub-Station Name: Kasba 220 KV
Select Date : 2025-01-14
Select Date in the Format of YYYY-MM-DD (e.g. - 2024-01-17)
DOWNLOAD



WBSETCL

West Bengal State Electricity Transmission Company Limited
A Government of West Bengal Enterprise

CIN No. U40101WB2007SGC113474

**Towering Heights
Illuminating Lives
Transmitting Happiness**

বিন্দুৎ স্রবহন রূপে,
বাংলা এখন আলোর পাশে

Approved Log Register of 2025-01-14

Time Dependent Equipment Parameters & Their Values

132 KV Transformer :- 132 KV 160 MVA TR. NO. III

05-06 Hrs	B-AMP	30	MVA	32	MVAR	33	MW	31	R-AMP	28	Y-AMP	29
-----------	-------	----	-----	----	------	----	----	----	-------	----	-------	----

132 KV Feeder :- KASBA-SALT LAKE-KLC - 2

05-06 Hrs	B-AMP	24	MVA	26	MVAR	27	MW	25	R-AMP	22	Y-AMP	23
-----------	-------	----	-----	----	------	----	----	----	-------	----	-------	----

132 KV Feeder :- KASBA-SONARPUR - 2

05-06 Hrs	B-AMP	36	MVA	38	MVAR	39	MW	37	R-AMP	34	Y-AMP	35
-----------	-------	----	-----	----	------	----	----	----	-------	----	-------	----

132 KV Transformer :- 132 KV 150 MVA TR. NO. I

05-06 Hrs	B-AMP	3	MVA	5	MVAR	6	MW	4	R-AMP	1	Y-AMP	2
-----------	-------	---	-----	---	------	---	----	---	-------	---	-------	---

132 KV Feeder :- KASBA-SONARPUR - 1

05-06 Hrs	B-AMP	42	MVA	44	MVAR	45	MW	43	R-AMP	40	Y-AMP	41
-----------	-------	----	-----	----	------	----	----	----	-------	----	-------	----

132 KV Bus :- 132 KV 150 MVA TR. NO. II

05-06 Hrs	B-R	21	R-Y	19	Y-B	20
-----------	-----	----	-----	----	-----	----

132 KV Feeder :- KASBA-SALT LAKE STADIUM - 2

05-06 Hrs	B-AMP	15	MVA	17	MVAR	18	MW	16	R-AMP	13	Y-AMP	14
-----------	-------	----	-----	----	------	----	----	----	-------	----	-------	----

220 KV Transformer :- 220 KV 160 MVA TR. NO. IV

05-06 Hrs	B-AMP	48	MVA	50	MW	49	R-AMP	46	Y-AMP	47
-----------	-------	----	-----	----	----	----	-------	----	-------	----

Download Excel version of Log Register

User can Download the Excel version of Log Register once the Log Register of any Particular Date, which is approved by the Station in-Charge by OTP validation Approach by clicking in the “**Download (Excel)**” Button at the side panel of the Page.

	A	B	C	D	E	F	G	H	I
1	Sub-Station	Date	Time Slot	Voltage Class	Bay Type	Bay Name	Parameter Name	Parameter Value	
2	Kasba 220 KV	2025-01-14	05-06 Hrs	132	Transformer	132 KV 150 MVA TR. NO. I	B-AMP	3	
3	Kasba 220 KV	2025-01-14	05-06 Hrs	132	Transformer	132 KV 150 MVA TR. NO. I	MVA	5	
4	Kasba 220 KV	2025-01-14	05-06 Hrs	132	Transformer	132 KV 150 MVA TR. NO. I	MVAR	6	
5	Kasba 220 KV	2025-01-14	05-06 Hrs	132	Transformer	132 KV 150 MVA TR. NO. I	MW	4	
6	Kasba 220 KV	2025-01-14	05-06 Hrs	132	Transformer	132 KV 150 MVA TR. NO. I	R-AMP	1	
7	Kasba 220 KV	2025-01-14	05-06 Hrs	132	Transformer	132 KV 150 MVA TR. NO. I	Y-AMP	2	
8	Kasba 220 KV	2025-01-14	05-06 Hrs	132	Bus	132 KV 150 MVA TR. NO. II	B-R	21	
9	Kasba 220 KV	2025-01-14	05-06 Hrs	132	Bus	132 KV 150 MVA TR. NO. II	R-Y	19	
10	Kasba 220 KV	2025-01-14	05-06 Hrs	132	Bus	132 KV 150 MVA TR. NO. II	Y-B	20	

Digital Event Register

STEP 1:

Creation of Event Register (As and When Any Event Occurs):

- Go to Register->Event register & Login
- First select the Shift and then Enter the details like T.O Trip, T.O Closing, Relay Indication and Remarks. Remember Entire data for a particular shift must enter at a time.



West Bengal State Electricity Transmission Company Limited
 A Government of West Bengal Enterprise
CIN No. U40101WB2007SGC113474

Towering Heights
 Illuminating Lives
 Transmitting Happiness

বিদ্যুৎ সার্বজনীন স্বপ্ন,
 বাস্তবতা এখন আমাদের পাশে

Log Out

Details of Parameters and value Input Section:

Sub-Station Name:

Date of the Event :

Kindly Fill the Shift Wise Tripping Details: (Shift wise details can be enter during end of each Shift. e.g- Night shift data entry Time: 05-06 Hrs; Morning shift data entry Time: 13-14 Hrs and Evening shift data entry Time: 21-22 Hrs)

Enter the Shift

Sl No.	Equipment Type	Equipment Name	T.O Trip	T.O Closing	Relay Indication	Remarks (Max 80 Characters)
1	132 KV BUS	132 KV 150 MVA TR. NO. II				
2	132 KV BUS	132 KV BUS VOLTAGE				
3	220 KV BUS	220 KV BUS VOLTAGE				
4	132 KV FEEDER	KASBA-SONARPUR -1				
5	132 KV FEEDER	KASBA-CESC - 1				
6	132 KV FEEDER	KASBA-CESC - 2				
7	132 KV FEEDER	KASBA-CESC - 3				
8	220 KV FEEDER	Kasba-CESC 2				
9	132 KV FEEDER	KASBA-SALT LAKE - 1				

- For Multiple Tripping of any equipment, first fill the upper section and then choose only equipment that are facing multiple tripping and fill the data and click on “SAVE” button after ticking the disclaimer.

25	132 KV TRANSFORMER	160 MVA Tr. No. 4	102	54	45	No Tripping
26	132 KV TRANSFORMER	160 MVA Tr. No. 3	82	89	74	Excellent

Details of Equipment wise Multiple Tripping Records (If Applicable):

Choose the Equipment for Multiple Tripping Incidents:

Salt Lake Stadium FDR- II 52 27 107 Good

150 MVA Tr. No. 1 56 38 67 Better

Remove

Add More Tripping Details

After Saving, “Logout” from the Page.

STEP 2:

Display of Event Register:

First click on “Event Register” button at Left Menu. Then Select the Date and press on the ‘SHOW’ Button to see the Event of a particular date.



West Bengal State Electricity Transmission Company Limited
A Government of West Bengal Enterprise
CIN No. U40101WB2007SGC113474

Towering Heights
Illuminating Lives
Transmitting Happiness

বিদ্যুৎ সংবহন রথে,
বাংলা এখন আলোর পথে

Dashboard

Log Register

Event Register

Download Log Register

Download Event Register

Download (Excel)

Reports

Logout

Digital Event Register

Sub-Station Name: Kasba 220 KV

Select Date : 2025-01-14

Select Date in the Format of YYYY-MM-DD (e.g., 2024-01-17)

SHOW

Selected Date: 2025-01-14 (Event Register)

Shift Timing	Voltage classwise Bay Type	Bay Name	T.O Trip	T.O Closing	Relay Indication	Remarks
05-06 Hrs	132 KV TRANSFORMER	132 KV 150 MVA TR. NO. I				
05-06 Hrs	132 KV BUS	132 KV 150 MVA TR. NO. II	1	2	3	Shutdown
05-06 Hrs	132 KV BUS	132 KV 150 MVA TR. NO. II	10	11	12	Excell Voltage
05-06 Hrs	132 KV TRANSFORMER	132 KV 160 MVA TR. NO. III				
05-06 Hrs	132 KV TRANSFORMER	132 KV 160 MVA TR. NO. IV				
05-06 Hrs	132 KV BUS	132 KV BUS VOLTAGE	4	5	6	Normal
05-06 Hrs	132 KV FEEDER	KASBA-CESC - 1				
05-06 Hrs	132 KV FEEDER	KASBA-CESC - 2				
05-06 Hrs	132 KV FEEDER	KASBA-CESC - 3				
05-06 Hrs	132 KV FEEDER	KASBA-SALT LAKE - 1				
05-06 Hrs	132 KV FEEDER	KASBA-SALT LAKE STADIUM - 1				
05-06 Hrs	132 KV FEEDER	KASBA-SALT LAKE STADIUM - 2				
05-06 Hrs	132 KV FEEDER	KASBA-SALT LAKE-KLC - 2				
05-06 Hrs	132 KV FEEDER	KASBA-SONARPUR - 2				
05-06 Hrs	132 KV FEEDER	KASBA-SONARPUR - 1				
05-06 Hrs	220 KV 150 MVA TR. NO. I	220 KV 150 MVA TR. NO. I				

Download PDF version of Event Register:

Choose the Download Event Register form the Left Menu then choose the date and press on the “DOWNLOAD” Button to download the PDF format of the event Register of a Date.



West Bengal State Electricity Transmission Company Limited
 A Government of West Bengal Enterprise
 CIN No. U40101WB2007SGC113474

Towering Heights
 Illuminating Lives
 Transmitting Happiness

বিদ্যুৎ সংবহন রথে,
 বাংলা এখন আলোর পথে

Dashboard
 Log Register
 Event Register
 Download Log Register
 Download Event Register
 Download (Excel)
 Reports
 Logout

[Download Event Register](#)

 Sub-Station Name:
 Select Date : Select Date in the Format of YYYY-MM-DD (e.g.- 2024-01-17)

DOWNLOAD



West Bengal State Electricity Transmission Company Limited
 A Government of West Bengal Enterprise
 CIN No. U40101WB2007SGC113474

Towering Heights
 Illuminating Lives
 Transmitting Happiness

বিদ্যুৎ সংবহন রথে,
 বাংলা এখন আলোর পথে

Digital Event Register of Kasba 220 KV for the Day of 2025-01-14

Shift Timing	Voltage Class	Bay Name	Bay Name	T.O Trip	T.O Closing	Relay Indication	Remarks
05-06 Hrs	132 KV Voltage	TRANSFORMER	132 KV 150 MVA TR. NO. I				
05-06 Hrs	132 KV Voltage	BUS	132 KV 150 MVA TR. NO. II	1	2	3	Shutdown
05-06 Hrs	132 KV Voltage	BUS	132 KV 150 MVA TR. NO. II	10	11	12	Excell Voltage
05-06 Hrs	132 KV Voltage	TRANSFORMER	132 KV 160 MVA TR. NO. III				
05-06 Hrs	132 KV Voltage	TRANSFORMER	132 KV 160 MVA TR. NO. IV				
05-06 Hrs	132 KV Voltage	BUS	132 KV BUS VOLTAGE	4	5	6	Normal
05-06 Hrs	132 KV Voltage	FEEDER	KASBA-CESC - 1				

Reports

Various Reports as per User Requirement will appear in this section in due course.

Logout

Once all done Logout from the Dashboard.

Frequently Asked Questions (FAQ):

Q. Can I Add New voltage class, if I forgot to add in earlier stage or in commissioning of a new voltage class?

A. Yes. Please refer to Page 4 STEP 2.

Q. Can I Change the Equipment Name Spelling or Change wrongly entered voltage class/Bay Type?

A. Yes. Please refer to Page 3 Step 2.

Q. New Application is not opening using URL- www.eregister.wbsetcl.in, Why?

A. Please clear the CACHE of the browser and retry again to opening the Application.

Q. What is the significance of 'Panel sequence' in the Equipment Master Page?

A. Bay / Panel sequence in which reading is taken in the concern sub-station- Required to maintain for ease of reading entry. All the Equipment must have panel sequence starting from 1 to higher number. Panel sequence 1 will come first in the log register page.

Q. Where we have to enter shift wise Data?

A. Main Log Register, Weather Register and Event Register.

Q. How to enter data in the main log register form?

A. Start entering data from Top to down order. If your Log Register is Big in size (More than 250 Rows) then Save as Draft the data Temporarily basis pressing 'Ctrl+S' shortcut key. Once you feel the entire data entry for s selected timeslot is completed the, Save the data Permanently.

Q. What if you don't save the data Permanently?

A. If you don't save the data Finally /Permanently then on the next day you are unable to save the data for previous date. As a result, data will be left as a draft for ever and Log register data **will not** be feasible to approve, print (either in PDF/Excel format).

Q. How to enter the data in Weather register?

A. Shift wise details can be entered during end of each Shift. e.g.- Night shift data entry Time: 05-06 Hrs; Morning shift data entry Time: 13-14 Hrs and Evening shift data entry Time: 21-22 Hrs. Without Entering Night Shift Data of the Day, you are Unable to Insert data for Morning or Evening Shift Data.

Q. Can I enter Event Register of a day several times?

A. No, Event register data whether single or multiple tripping must enter in shift wise. Once shift is over you are unable to enter data for previous shift of the day.

Q. What are the data need to be entered in the Transformer Register?

A. Only TAP count required to be entered, rest opening balance and closing balance will be automatically evaluated. However, for the first time user need to enter current closing balance in the TAP count and from the next day today's closing balance will be reflected in the next day's opening balance.

Q. What if OTP will not come for Log Register Approval?

A. OTP will come to Mail (SPAM), but if not delivered, kindly check top of the page where, OTP is written.

Q. When we can download Log register Data?

A. Once the Log register of a Particular date is approved, then only user is able to download the Log Register of the day in PDF or Excel format.

Q. How long old data will be available in the website.

A. Maximum of tenure of 3 Months. Thus, all SS are requested to download Log register data in regular interval and keep in safe place as a Backup.